TAJFUN 1000 432 MHz





PA TAJFUN 1000 900W 432MHz

Rating: Not Rated Yet
Price:
Sales price without tax: 2162,00 €

Ask a question about this product

Manufacturer: VH Electronics

Description

New robust Heatsink - Fischer. Output power 900W CW.
LAN & USB as standard.



TAJFUN 1000 is small, lightweight but robus LDMOS Power Amplifier

- Freqency Coverage: 430-434 MHz
- Operating Mode: FM, CW, SSB, DIGI
- Output Power: 900W CW, 700W SSB, 600W FM and DIGI modes 50% duty cycle
- Input Power: 18-20W, install 3dB attenuator (option 6dB)
- Power supply inside: 53VDC / 1800W
- Suppression of harmonics: >= 70dBc
- Low Pass Filter
- Working temperature: 0-45 °C, Max. humidity 90%
- Protection from: PWR, SWR, Tmax, Imax, Umax/Umin
- Control / Display: color TFT display
- 3x temperature PWM controlled fans + small turbine
- Measurment and display:
    - Current
    - Voltage
    - Power
    - Reflected power
    - Peak power
    - Temperature
- USB - configuration, service
- LAN - remote
- Power supply: 195-277VAC, 45-66Hz
- Dimension: 266x105x294mm
- Coaxial Relay: CX600NC - CX140D (without relay as option)
- Weight: 6,2kg

Instruction manual:

TAJFUN 1000 432.pdf

Software:

Tajfun 1000 servis (ver.: 1.0.3.3)

Tajfun 1000 Remote Display (ver.: 1.0.0.5)

Tajfun 1000 Remote Display (ver.: 1.0.0.6)

Tajfun 1000 Remote Display (ver.: 1.0.0.8)